TEKNOFLOOR AQUA 110F A -EPOXY SYSTEM

1 25.02.2021

Intended to be used in nuclear power stations as a protective coating system for concrete floors. The system consists of chemically curing water-borne two-pack epoxy paint. The system comes up to the specifications of STUK-YTO-TR 210 (Research Report VTT-CR-01512-20 by the Technical Research Centre of Finland).

The coating system structure:	EP180/3
TEKNOFLOOR AQUA 110F A Concrete Paint	3 x 60 µm
Total film thickness	180 µm

USAGE For protection of concrete surfaces in nuclear power stations in controlled indoor areas that are exposed to radiation and decontamination in spaces subjected to minor mechanical wear.

Surface preparation New concrete floor: New concrete must be at least 4 weeks old and well-hardened so that all moisture from casting is bound and the surface dry. The moisture of the concrete must not exceed 97 % as relative humidity or 4% by weight (by 54 / BLY 12).

Surface grinding is the best method to remove laitance. It is always recommended for industrial floors and it is done on new industrial floors as wet grinding in connection with casting. Brittle and powdery top layers are ground so that the solid concrete containing aggregates is exposed. Remove all cement dust by vacuum cleaning or brushing.

Old concrete floor: Uncoated, greasy floors can be cleaned by emulsion wash. After the emulsion wash flaking old paint coats and possible laitance is removed by diamond grinding.

ApplicationMixing of the paint: Mix 1 part Base to 1 part Hardener by volume immediately before use and
stir thoroughly. Stir the Base before mixing so that it is homogenous. If the quantity of the
mixture is more than 1 liter, use a slow-rotating hand drilling machine. Inadequate stirring or
incorrect mixing ratio results in imperfect curing and impaired film properties. Ready paint is to
be used within 1½ h from mixing. After this the mixture is unfit for use.

Apply two coats to new concrete floors. Dilute the paint for priming by adding 5 - 10% water. The paint is diluted by water, which is added to the ready paint mixture. Apply the paint generously so that the porous concrete surface is sealed. Solvents must not be used for diluting!

Apply by brush, short-piled mohair roller or airless spray. Use airless spray nozzles 0.015 - 0.018". Clean all equipment immediately after use with water and detergent.

The technical data of the paint are given in the table below and in the product data sheet.

РТО

Maintenance Repair, maintenance and renewal painting is done according to separate instructions given for the nuclear power plant, observing valid local orders issued by the authorities.

Technical Data

Paint		TEKNOFLC 110F A	OR AQUA
Data Sheet	No.	1254	
Paint Type		two-pack water-borne epoxy paint	
Colours		by agreement	
Finish		gloss	
Thinner		water	
Methods of application		brush, roller, airless spray	
Airless spray nozzle		0.015 – 0.018"	
Application conditions			
- min. temperature	°C	+10	
- max. relative humidity	%	70	
Safety markings		See Safety Data Sheet	
Volume solids	%	45 ±2	
Total mass of solids	g/l	abt. 650	
Volatile organic compound	ł		
(VOC) g/l		20	
Recommended film thickn	ess		
- wet	μm	133	
- dry	μm	60	
Theoretical spreading rate m²/l		7.5	
Drying time, +23°C / 50 % RH		(dry film 60 µm)	
- dust free (ISO 9117-3:2010)		after 1 h	
- fit for light traffic		after 4 h	
Overcoatable, 50% RH		by itself:	
		min.	max.*
+1	0°C	after 12 h	after 7 d
+2	23°C	after 4 h	after 7 d

* Maximum overcoating interval without roughening.